

## Mini UHF Female to BNC Male Adapter

Mini UHF female to BNC male adapter part number SM2233 from Fairview Microwave is in-stock and ships same day. This Fairview Mini UHF to BNC adapter has a female to male gender configuration. SM2233 Mini UHF female to BNC male adapter operates to 2.5 GHz.

RF adapters can be used to enable connections between two connector types that would otherwise not mate. Certain RF adapter configurations can also be used to protect connectors on expensive equipment where the number of connect and disconnect cycles is high. An RF, microwave, or millimeter wave adapter is connected to the equipment and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Fairview Microwave also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

### Electrical Specifications

Description	Min	Typ	Max	Units
Frequency Range	DC		2.5	GHz
DWV (AC)			335	Vrms

### Mechanical Specifications

<b>Size</b>	
Length	1.216 in [30.89 mm]
Weight	0.0305 lbs [13.83 g]

Description	Connector 1	Connector 2
Type	Mini UHF Female	BNC Male
Polarity	Standard	Standard

### Material Specifications

Description	Connector 1	Connector 2
Type	Mini UHF Female	BNC Male
Contact Material	Brass	Brass
Contact Plating	Gold	Gold
Insulation Material	PTFE	PTFE
Body Material	Brass	Brass
Body Plating	Nickel	Nickel

**Compliance Certifications** (see [product page](#) for current document)

### Plotted and Other Data

Notes:



### Configuration:

- Mini UHF Female Connector 1
- BNC Male Connector 2
- 50 Ohm
- Straight Body Geometry

### Features:


- Gold Plated Brass Contact

### Applications:

- Enables Between Series Connections
- General Purpose Test

Fairview Microwave  
 1130 Junction Dr. #100  
 Allen, TX 75013  
 Tel: 1-800-715-4396 / (972) 649-6678  
 Fax: (972) 649-6689  
[www.fairviewmicrowave.com](http://www.fairviewmicrowave.com)  
[sales@fairviewmicrowave.com](mailto:sales@fairviewmicrowave.com)

**Typical Performance Data**




Mini UHF Female to BNC Male Adapter from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: [Mini UHF Female to BNC Male Adapter SM2233](#)

URL: <https://www.fairviewmicrowave.com/mini-uhf-female-bnc-male-adapter-sm2233-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.



STANDARD TOLERANCES	
.X	±0.2
.XX	±0.1
.XXX	±0.05

\*STANDARD TOLERANCES APPLY ONLY TO DIMENSIONS IN INCHES

<b>FAIRVIEW MICROWAVE INC.</b> ALLEN, TX 75013 WWW.FAIRVIEWMICROWAVE.COM		NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].			
TITLE Mini UHF Female to BNC Male Adapter		DWG NO SM2233		CAGE CODE 3FKR5	
CAD FILE	052517	SHEET	SCALE	N/A	SIZE A 2233